

ASTi Telestra Cold Start Procedure

Overview

The cold start procedure described in this document allows users to build Telestra systems from scratch. There are two main reasons for using the cold start procedure:

1. Rebuilding a damaged hard disk
2. Creating spare hard disks

Requirements

For systems *with* a built-in CD-ROM drive, use the procedure outlined on pages 2-3. You will need the following items:

- ASTi Software CD

For systems *without* a built-in CD-ROM drive, use the procedure outlined on page 4. You will need the following items:

- ASTi Kickstart Diskette
- ASTi Linux CD
- ASTi Telestra CD
- USB CD-ROM kit:
 - USB CD-ROM drive & power cable
 - USB connection cable

Cold Start Procedure: Built-In CD-ROM Drive

WARNING: *This will COMPLETELY ERASE the contents of your hard drive.*

Before beginning, make sure you have a hard drive properly inserted into the system, along with a connected monitor and keyboard.

Configuring the Award BIOS for MX3S and MX3S-T AOpen motherboards

The following instructions apply to the 1U Telestra chassis with built-in CD-ROM drive and *Award BIOS for MX3S and MX3S-T AOpen* motherboards. See the next section for instructions on configuring BIOS version CA81020A.86A.0006.P03.

1. Immediately after system power-on or reboot, press the Delete or Del key to enter BIOS setup.
2. From the main screen, verify title reads, “CMOS Setup Utility - Copyright (C) 1984-2001 Award Software”.
3. Press the right-arrow key to highlight “Load Setup Defaults” (first option, right-hand column), and press the ENTER key.
4. Confirm the action by typing “Y”, followed by the ENTER key.
5. Use the arrow keys to highlight “Advanced BIOS Features” (second option, left-hand column), and press the ENTER key to access those settings.
6. Make sure the “First Boot Device” is set to “CDROM”, which is the default.
7. Press the ESC key to return to the main menu. Use the down-arrow key to select “Integrated Peripherals” (fourth option, left-hand column).
8. Change the “IDE Primary Master UDMA”, “IDE Primary Slave UDMA”, “IDE Secondary Master UDMA”, and “IDE Secondary Slave UDMA” settings to “Disable”. For each, highlight the setting, press the ENTER key, arrow-down to “Disable” and press ENTER.
9. Press the F10 key to save the settings and exit the utility.
10. Confirm the action by typing “Y”, followed by the ENTER key.
11. The system will then reboot using the new BIOS settings. Proceed with “Installing Linux & Telestra Software” below.

Configuring BIOS version CA81020A.86A.0006.P03

The following instructions apply to the 1U Telestra chassis with built-in CD-ROM drive and BIOS version *CA81020A.86A.0006.P03*.

1. Immediately after system power-on or reboot, press the F2 key to enter BIOS setup.
2. From the main screen, verify BIOS version matches that listed above.
3. Press the F9 key to load BIOS defaults, followed by the ENTER key to confirm the action.
4. Use the right-arrow key to move the cursor over the “Boot” menu at the top of the screen; in the main window, boot settings will be displayed.
5. “Quiet Boot” will already be highlighted. Press ENTER to access this setting, use the up-arrow key to highlight “Disabled”, then press ENTER to change the setting.
6. Use the down-arrow key to highlight “2nd Boot Device”. Press ENTER to access this setting, use the down-arrow key to highlight “ATAPI CDROM”, and press ENTER to change the setting.
7. Use the down-arrow key to highlight “3rd Boot Device”. Press ENTER to access this setting, use the up-arrow key to highlight “IDE-HDD”, and press ENTER to change the setting.
8. Press the F10 key to save the settings and exit the utility; press ENTER to confirm the action. The system will then reboot using the new BIOS settings. Proceed with software installation.

Installing Linux & Telestra Software

1. Turn on the Telestra system via the power switch on the front of the chassis.
The system may or may not fully boot, and you may receive an error message.
2. Insert the CD labeled “ASTi Software CD” into the CD-ROM drive.
3. Reboot the system using the “Reset” button on the front of the chassis.
4. The system will boot from the CD, and the Linux Base System will begin to install. You will see a dialog box showing the progress of this installation.
5. After Base System installation, the CD-ROM drive will open, and the screen will display a “Reboot the system?” confirmation.
 - a. Remove the CD. ***Failure to do this will result in Base System reinstallation.***
 - b. Press the ENTER key to confirm system reboot.
6. After reboot, the screen will display “ASTi Software Installation”. Open the CD-ROM drive, insert the same “ASTi Software CD”, and press the ENTER key. The drive will close, and installation will proceed.
7. Upon completion, the CD-ROM drive will open, and the screen will display a “Finish ASTi Installation” confirmation.
 - a. Remove the CD. ***Failure to do this will result in Base System reinstallation.***
 - b. Press the ENTER key to confirm, and the system will reboot.

Cold Start Procedure: USB CD-ROM Drive

WARNING: *This will COMPLETELY ERASE the contents of your hard drive.*

Before beginning, make sure you have a hard drive properly inserted into the system, along with a connected monitor and keyboard.

Installing Linux

1. Connect the USB CD-ROM and power cable to power source. Then, connect the USB CD-ROM drive to the Telestra system using the USB connector cable. The USB port is on the front of the Telestra chassis.
2. Insert the floppy disk labeled “ASTi Kickstart Diskette”.
3. Turn on the Telestra system via the power switch on the front of the chassis. The system will boot from the floppy.
4. Insert the CD labeled “ASTi Linux CD”.
5. Linux will begin to install, and you will see a dialog box showing the progress of the installation.

If you see a message indicating a Bad Partition Table, select the “Initialize” option to continue with the Linux installation.

6. A message will then be displayed indicating the install has finished.

If you want to install ASTi software, skip to step 2 of the next section: “Installing ASTi Software”.

- OR -

7. Remove the “ASTi Kickstart Diskette”.
8. Press ENTER to reboot the system.
9. Remove the “ASTi Linux CD” after it ejects.

Installing ASTi Software

1. Connect the USB CD-ROM drive as in step 1 of “Installing Linux” above.
2. Power on the system (or, if you have just finished installing Linux, remove the “ASTi Kickstart Diskette” and press ENTER to reboot, then remove the “ASTi Linux CD” after it ejects.).
3. Insert the CD labeled “ASTi Software CD”.
4. At the “LILO:” prompt, type “asti” and press ENTER. If you miss the “LILO:” prompt, you will need to reboot by pressing the CTRL + ALT + DEL keys.
5. ASTi software installation will proceed. After a while, a message will display indicating the installation has completed.
6. Remove the “ASTi Software CD”, disconnect the CD-ROM drive, and press ENTER to reboot the system.